



INTERNATIONAL STANDARD ISO/IEC 14496-3:2009 TECHNICAL CORRIGENDUM 3

Published 2012-09-01

INTERNATIONAL ORGANIZATION FOR STANDARDIZATION • МЕЖДУНАРОДНАЯ ОРГАНИЗАЦИЯ ПО СТАНДАРТИЗАЦИИ • ORGANISATION INTERNATIONALE DE NORMALISATION
INTERNATIONAL ELECTROTECHNICAL COMMISSION • МЕЖДУНАРОДНАЯ ЭЛЕКТРОТЕХНИЧЕСКАЯ КОМИССИЯ • COMMISSION ÉLECTROTECHNIQUE INTERNATIONALE

Information technology — Coding of audio-visual objects — Part 3: Audio

TECHNICAL CORRIGENDUM 3

Technologies de l'information — Codage des objets audiovisuels

Partie 3: Audio

RECTIFICATIF TECHNIQUE 3

Technical Corrigendum 3 to ISO/IEC 14496-3:2009 was prepared by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 29, *Coding of audio, picture, multimedia and hypermedia information*.

In 12.3 Payloads for the audio object, replace Table 12.2:

Syntax	No. of bits	Mnemonics
<pre>lle_element() { for (ch=0;ch<channel_number;) { if (is_channel_pair(ch)) { lle_channel_pair_element(); ch += 2; } else { lle_single_channel_element(); ch++; } } }</pre>		

with:

Syntax	No. of bits	Mnemonics
<pre> lle_element() { for (el=0; el<getNrOfElements(channelConfiguration);) { switch(getNextElement(el, channelConfiguration)){ case LLE_SCE: lle_single_channel_element(); break; case LLE_LFE: lle_lfe_channel_element(); break; case LLE_CPE: lle_channel_pair_element(); break; } el++; } } </pre>		

In 12.3 Payloads for the audio object, add at the end:

Table 12.9 — Syntax of lle_lfe_channel_element

Syntax	No. of bits	Mnemonics
<pre> lle_lfe_channel_element() { lle_individual_channel_stream(1); } </pre>		

In 12.3 Payloads for the audio object, add at the end:

The functions `getNrOfElements(channelConfiguration)` and `getNextElement(el, channelConfiguration)` are defined as follows:

```

UINT32 getNrOfElements(channelConfiguration)
{
    UINT32 NrOfFixChannelConfigElements[7] = { 1, 1, 2, 3, 3, 4, 5 };

    if(channelConfiguration == 0){
        return num_front_channel_elements + num_side_channel_elements +
            num_back_channel_elements + num_lfe_channel_elements;
    } else {
        return NrOfFixChannelConfigElements[channelConfiguration - 1];
    }
}

```

```

    }
}

typedef enum {

    LLE_SCE = 0,

    LLE_CPE,

    LLE_LFE,

    LLE_INV      /*dummy element for array */
} LLE_Element;

LLE_Element getNextElement(el, channelConfiguration)
{
    LLE_Element FixChannelConfigElements[7][5] =
    { {LLE_SCE, LLE_INV, LLE_INV, LLE_INV, LLE_INV},
      {LLE_CPE, LLE_INV, LLE_INV, LLE_INV, LLE_INV},
      {LLE_SCE, LLE_CPE, LLE_INV, LLE_INV, LLE_INV},
      {LLE_SCE, LLE_CPE, LLE_SCE, LLE_INV, LLE_INV},
      {LLE_SCE, LLE_CPE, LLE_CPE, LLE_INV, LLE_INV},
      {LLE_SCE, LLE_CPE, LLE_CPE, LLE_LFE, LLE_INV},
      {LLE_SCE, LLE_CPE, LLE_CPE, LLE_CPE, LLE_LFE} };

    if(channelConfiguration == 0){

        UINT el_cnt = 0, el_front = 0, el_side = 0, el_back = 0, el_lfe = 0;

        for(; el_front < num_front_channel_elements; el_cnt++, el_front++){

            if(el_cnt == el){

                if(front_element_is_cpe[el_front] == 1){

                    return LLE_CPE;

                } else {

                    return LLE_SCE;

                }

            }

        }

    }
}

```

```

for(;el_side < num_side_channel_elements; el_cnt++, el_side++){
    if(el_cnt == el){
        if(side_element_is_cpe[el_side] == 1){
            return LLE_CPE;
        } else {
            return LLE_SCE;
        }
    }
}

for(;el_back < num_back_channel_elements; el_cnt++, el_back++){
    if(el_cnt == el){
        if(back_element_is_cpe[el_back] == 1){
            return LLE_CPE;
        } else {
            return LLE_SCE;
        }
    }
}

for(;el_lfe < num_lfe_channel_elements; el_cnt++, el_lfe++){
    if(el_cnt == el){
        return LLE_LFE;
    }
}
} else {
    return FixChannelConfigElements [channelConfiguration - 1][el];
}

return LLE_INV;
}

```