

Second edition
2004-09-15

AMENDMENT 7
2015-11-15

**Information technology — JPEG 2000
image coding system: Core coding
system**

**AMENDMENT 7: Profiles for an
interoperable master format (IMF)**

*Technologies de l'information — Système de codage d'images JPEG
2000: Système de codage de noyau*

AMENDEMENT 7:.

IECNORM.COM : Click to view the full PDF of ISO/IEC 15444-1:2004/Amd7:2015

IECNORM.COM : Click to view the full PDF of ISO/IEC 15444-1:2004/AMD7:2015



COPYRIGHT PROTECTED DOCUMENT

© ISO/IEC 2015, Published in Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
Ch. de Blandonnet 8 • CP 401
CH-1214 Vernier, Geneva, Switzerland
Tel. +41 22 749 01 11
Fax +41 22 749 09 47
copyright@iso.org
www.iso.org

CONTENTS

	<i>Page</i>
1) Table A.10	1
2) Table A.49 and additional Tables A.50-A.54	2
3) Table M.1	6
4) Clause M.4	6
M.4 Elementary stream marker box (superbox)	6
5) Table M.2	7
6) Clause M.4.6	7
7) References	8
8) Bibliography (clause K)	8

IECNORM.COM : Click to view the full PDF of ISO/IEC 15444-1:2004/Amd7:2015

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work. In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1.

International Standards are drafted in accordance with the rules given in the ISO/IEC Directives, Part 2.

The main task of the joint technical committee is to prepare International Standards. Draft International Standards adopted by the joint technical committee are circulated to national bodies for voting. Publication as an International Standard requires approval by at least 75 % of the national bodies casting a vote.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights.

ISO/IEC 15444-1:2004/Amd 7 was prepared by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 29, *Coding of audio, picture, multimedia and hypermedia information*, in collaboration with ITU-T. The identical text is published as ITU-T T.800 (10/2014).

**INTERNATIONAL STANDARD
ITU-T RECOMMENDATION**

**Information technology – JPEG 2000 image coding system:
Core coding system**

Amendment 7

Profiles for an interoperable master format (IMF)

1) Table A.10

Replace Table A.10 with the following table:

Table A.10 – Capability Rsiz parameter

Value (bits)		Capability
MSB	LSB	
0000	0000 0000 0000	Any capabilities specified in this Recommendation International Standard
0000	0000 0000 0001	Codestream restricted as described for Profile 0 from Table A.45
0000	0000 0000 0010	Codestream restricted as described for Profile 1 from Table A.45
0000	0000 0000 0011	2k Digital Cinema Profile as specified in Table A.46
0000	0000 0000 0100	4k Digital Cinema Profile as specified in Table A.46
0000	0000 0000 0101	Scalable 2k Digital Cinema Profile as specified in Table A.46
0000	0000 0000 0110	Scalable 4k Digital Cinema Profile as specified in Table A.46
0000	0000 0000 0111	Long-term storage Profile as specified in Table A.46
0000	0001 0000 xxxx	Broadcast Contribution Single Tile Profile as specified in Table A.48, lower 8Bits identify Mainlevel as described in Table A.49
0000	0010 0000 xxxx	Broadcast Contribution Multi-tile Profile as specified in Table A.48, lower 8Bits identify Mainlevel as described in Table A.49
0000	0011 0000 0110	Broadcast Contribution Multi-tile Reversible Profile as specified in Table A.48, Mainlevel 6 as described in Table A.50
0000	0011 0000 0111	Broadcast Contribution Multi-tile Reversible Profile as specified in Table A.48, Mainlevel 7 as described in Table A.50
0000	0100 yyyy xxxx	2k IMF Single Tile Lossy Profile as specified in Table A.51, lower 8 Bits identify Sublevel and Mainlevel as specified in Table A.53 and A.54
0000	0101 yyyy xxxx	4k IMF Single Tile Lossy Profile as specified in Table A.51, lower 8 Bits identify Sublevel and Mainlevel as specified in Table A.53 and A.54
0000	0110 yyyy xxxx	8k IMF Single Tile Lossy Profile as specified in Table A.51, lower 8 Bits identify Sublevel and Mainlevel as specified in Table A.53 and A.54
0000	0111 yyyy xxxx	2k IMF Single/Multi Tile Reversible Profile as specified in Table A.52, lower 8 Bits identify Sublevel and Mainlevel as specified in Table A.53 and A.54
0000	1000 yyyy xxxx	4k IMF Single/Multi Tile Reversible Profile as specified in Table A.52, lower 8 Bits identify Sublevel and Mainlevel as specified in Table A.53 and A.54
0000	1001 yyyy xxxx	8k IMF Single/Multi Tile Reversible Profile as specified in Table A.52, lower 8 Bits identify Sublevel and Mainlevel as specified in Table A.53 and A.54
zzzz	yyyy xxxx	All other values reserved for future use by ITU-T ISO/IEC
zzzz describe Profile, yyyy describe Sublevel, xxxx describe Mainlevel.		

2) **Table A.49 and additional Tables A.50-A.54**

Replace Table A.49 and add additional Tables A.50-A.54.

Table A.49 – Operating levels for the broadcast contribution single tile and multi-tile profiles

Sampling Rate = (Average Components / Pixel) × (pixels / line) × (total lines / frame) × (frames / sec)

Where Average Components is two for 4:2:2, three for 4:4:4 or 4:2:2:4, and four for 4:4:4:4

Levels	Max. Components Sampling Rate (MSamples/sec)	Max. compressed Bit Rate [#] (Mbits/sec)
Mainlevel 0	Unspecified	Unspecified
Mainlevel 1	65	200
Mainlevel 2	130	200
Mainlevel 3	195	200
Mainlevel 4	260	400
Mainlevel 5	520	800
Mainlevel 6	1200	1600
Mainlevel 7	2400	3200
Mainlevel 8	4800	6400
Mainlevel 9	9600	12800
Mainlevel 10	19200	25600
Mainlevel 11	38400	51200
# Max. compressed bit rate = Max. instantaneous bit rate Mega (M), in the context of this Specification, is 10 ⁶		

Table A.50 – Operating levels for broadcast contribution multi-tile reversible profile

Sampling rate = (Average components / pixel) × (pixels / line) × (total lines / frame) × (frames / sec)

Where Average components is two for 4:2:2, three for 4:4:4 or 4:2:2:4, and four for 4:4:4:4

Levels	Max. components sampling rate (MSamples/sec)	Max. compressed bit rate [#] (Mbits/sec)
Mainlevel 6	520	1600
Mainlevel 7	520	Unspecified
# Max. compressed Bit Rate = Max. instantaneous Bit Rate Mega (M), in the context of this Specification, is 10 ⁶		

Table A.51 – Codestream restrictions for interoperable master format (IMF) single tile profiles

	2k IMF single tile lossy profile	4k IMF single tile lossy profile	8k IMF single tile lossy profile
SIZ marker segment			
Profile indication	See Table A.10	See Table A.10	See Table A.10
Image size	Xsiz ≤ 2048, Ysiz ≤ 1556	Xsiz ≤ 4096, Ysiz ≤ 3112	Xsiz ≤ 8192, Ysiz ≤ 6224
Tiles	One tile for the whole image: YTsiz + YTOsiz ≥ Ysiz XTsiz + XTOsiz ≥ Xsiz	Same	Same
Image and tile origin	XOsiz = YOsiz = XTOsiz = YTOsiz = 0	Same	Same
Sub-sampling	(XRsiz ¹ = 1 for all components) or (XRsiz ¹ = 1, XRsiz ² = 2 for remaining components).	Same	Same

Table A.51 – Codestream restrictions for interoperable master format (IMF) single tile profiles

	2k IMF single tile lossy profile	4k IMF single tile lossy profile	8k IMF single tile lossy profile
	$YR_{siz}^1 = 1$		
Number of components	$C_{siz} \leq 3$	Same	Same
Bitdepth	$7 \leq S_{siz}^i \leq 15$ (8-16 bits unsigned)	Same	Same
RGN marker segment	Disallowed, i.e., no region of interest	Same	Same
Marker locations			
Packed headers (PPM, PPT)	Disallowed	Same	Same
COD, COC, QCD, QCC	Main header only	Same	Same
COD/COC marker segments			
Number of decomposition levels	$1 \leq N_L \leq 5$ Every component of every image of a codestream shall have the same number of wavelet transform levels. The number of deployed decomposition levels shall be set accordingly in all COD and COC markers.	$1 \leq N_L \leq 6$ Every component of every image of a codestream shall have the same number of wavelet transform levels. The number of deployed decomposition levels shall be set accordingly in all COD and COC markers.	$1 \leq N_L \leq 7$ Every component of every image of a codestream shall have the same number of wavelet transform levels. The number of deployed decomposition levels shall be set accordingly in all COD and COC markers.
Number of layers	Shall be exactly 1	Same	Same
Code-block size	$xcb=ycb=5$ The corresponding values shall be set accordingly in all deployed COD and COC markers.	Same	Same
Code-block style	SPcod, SPcoc = 0000 0000	Same	Same
Transformation	9-7 Irreversible Transform	9-7 Irreversible Transform	9-7 Irreversible Transform
Precinct size	$PPx = PPy = 7$ for <i>NLL</i> band, else 8. The corresponding values shall be set accordingly in all COD and COC markers.	Same	Same
Progression order	CPRL, POC marker disallowed	Same	Same
Tile-parts	≤ 3 ; One for each component	Same	Same
Tile-part lengths	TLM marker segments are required in each image	Same	Same
Application specific restrictions			
Max. components sampling rate	See Table A.53	Same	Same
Max. compressed bit rate	See Tables A.53 and A.54 The maximum codestream size is the Max. compressed bit rate divided by the frame rate.	Same	Same

**Table A.52 – Codestream restrictions for interoperable master format (IMF)
single tile/multi-tile reversible profiles**

	2k IMF single/multi-tile reversible profile	4k IMF single/multi-tile reversible profile	8k IMF single/multi-tile reversible profile
SIZ marker segment			
Profile Indication	See Table A.10	See Table A.10	See Table A.10
Image size	$X_{siz} \leq 2048, Y_{siz} \leq 1556$	$X_{siz} \leq 4096, Y_{siz} \leq 3112$	$X_{siz} \leq 8192, Y_{siz} \leq 6224$
Tiles	One single tile for the whole image: $Y_{Tsiz} + Y_{TOsiz} \geq Y_{siz}$ $X_{Tsiz} + X_{TOsiz} \geq X_{siz}$ or multiple tiles with tile sizes: $X_{Tsiz} = Y_{Tsiz} = 1024$	One single tile for the whole image: $Y_{Tsiz} + Y_{TOsiz} \geq Y_{siz}$ $X_{Tsiz} + X_{TOsiz} \geq X_{siz}$ or multiple tiles with tile sizes: $X_{Tsiz} = Y_{Tsiz} = 1024$ or $X_{Tsiz} = Y_{Tsiz} = 2048$	One single tile for the whole image: $Y_{Tsiz} + Y_{TOsiz} \geq Y_{siz}$ $X_{Tsiz} + X_{TOsiz} \geq X_{siz}$ or multiple tiles with tile sizes: $X_{Tsiz} = Y_{Tsiz} = 1024$ or $X_{Tsiz} = Y_{Tsiz} = 2048$ or $X_{Tsiz} = Y_{Tsiz} = 4096$
Image and tile origin	$X_{Osiz} = Y_{Osiz} = X_{TOsiz} = Y_{TOsiz} = 0$	Same	Same
Sub-sampling	$(X_{Rsiz}^i = 1 \text{ for all components})$ or $(X_{Rsiz}^1 = 1, X_{Rsiz}^2 = 2 \text{ for remaining components}).$ $Y_{Rsiz}^1 = 1$	Same	Same
Number of components	$C_{siz} \leq 3$	Same	Same
Bitdepth	$7 \leq S_{siz}^i \leq 15$ (8-16 bits unsigned)	Same	Same
RGN marker segment	Disallowed, i.e., no region of interest	Same	Same
Marker locations			
Packed headers (PPM, PPT)	Disallowed	Same	Same
COD, COC, QCD, QCC	Main header only	Same	Same
COD/COC marker segments			
Number of decomposition levels	$1 \leq N_L \leq 4$ for $X_{Tsiz} \geq 1024$ or $1 \leq N_L \leq 5$ for $X_{Tsiz} \geq 2048$ Every component of every image of a codestream shall have the same number of wavelet transform levels. The number of deployed decomposition levels shall be set accordingly in all COD and COC markers.	$1 \leq N_L \leq 4$ for $X_{Tsiz} \geq 1024$ or $1 \leq N_L \leq 5$ for $X_{Tsiz} \geq 2048$ or $1 \leq N_L \leq 6$ for $X_{Tsiz} \geq 4096$ Every component of every image of a codestream shall have the same number of wavelet transform levels. The number of deployed decomposition levels shall be set accordingly in all COD and COC markers.	$1 \leq N_L \leq 4$ for $X_{Tsiz} \geq 1024$ or $1 \leq N_L \leq 5$ for $X_{Tsiz} \geq 2048$ or $1 \leq N_L \leq 6$ for $X_{Tsiz} \geq 4096$ or $1 \leq N_L \leq 7$ for $X_{Tsiz} \geq 8192$ Every component of every image of a codestream shall have the same number of wavelet transform levels. The number of deployed decomposition levels shall be set accordingly in all COD and COC markers.
Number of layers	Shall be exactly 1	Same	Same
Code-block size	$x_{cb} = y_{cb} = 5$ The corresponding values shall be set accordingly in all deployed COD and COC markers.	Same	Same
Code-block style	SPcod, SPcoc = 0000 0000	Same	Same

**Table A.52 – Codestream restrictions for interoperable master format (IMF)
single tile/multi-tile reversible profiles**

	2k IMF single/multi-tile reversible profile	4k IMF single/multi-tile reversible profile	8k IMF single/multi-tile reversible profile
Transformation	5-3 Reversible Transform	Same	Same
Precinct size	PPx = PPy = 7 for NLLL band, else 8. The corresponding values shall be set accordingly in all COD and COC	Same	Same
Progression order	CPRL, POC marker disallowed	Same	Same
Tile-parts	One tile-part per each tile component	Same	Same
Tile-part lengths	TLM marker segments are required in each image	Same	Same
Application specific restrictions			
Max. components sampling rate	See Table A.53	Same	Same
Max. compressed bit rate	See Tables A.53 and A.54 The maximum codestream size is the Max. compressed Bit rate divided by the frame rate.	Same	Same

Table A.53 – Operating levels for IMF profiles

Sampling rate = (Average components / Pixel) × (pixels / line) × (total lines / frame) × (frames / sec)

Where Average components is two for 4:2:2, three for 4:4:4 or 4:2:2:4, and four for 4:4:4:4

Levels	Max. components sampling rate (MSamples/sec)	Allowed sublevels (see Table A.54)
Mainlevel 0	Unspecified	Unspecified
Mainlevel 1	65	Sublevels 0 up to 1
Mainlevel 2	130	Sublevels 0 up to 1
Mainlevel 3	195	Sublevels 0 up to 1
Mainlevel 4	260	Sublevels 0 up to 2
Mainlevel 5	520	Sublevels 0 up to 3
Mainlevel 6	1200	Sublevels 0 up to 4
Mainlevel 7	2400	Sublevels 0 up to 5
Mainlevel 8	4800	Sublevels 0 up to 6
Mainlevel 9	9600	Sublevels 0 up to 7
Mainlevel 10	19200	Sublevels 0 up to 8
Mainlevel 11	38400	Sublevels 0 up to 9

Table A.54 – Operating sublevels for IMF profiles

Sublevels	Max. compressed Bit Rate # (Mbit/s)
Sublevel 0	unspecified
Sublevel 1	200
Sublevel 2	400
Sublevel 3	800
Sublevel 4	1600
Sublevel 5	3200
Sublevel 6	6400
Sublevel 7	12800
Sublevel 8	25600
Sublevel 9	51200
# Max. compressed bit rate = Max. instantaneous bit rate Mega (M), in the context of this Specification, is 10 ⁶	

3) Table M.1

Replace Table M.1 with the following table:

Box name	Type	Required	Comments
Elementary stream marker	'elsm' (0x656c736d)	Required if an Elementary stream is defined.	This marker precedes a series of boxes that contain header type information about the JPEG 2000 elementary stream
Frame rate box	'frat' (0x66726174)	Required	This box specifies the frame rate
Maximum bit rate box	'brat' (0x62726174)	Required	This box specifies the compressed bit rate
Field coding box	'fiel' (0x6669656c)	Optional	This box specifies interlacing
Time code box	'tcod' (0x74636f64)	Required	This box specifies time code
Broadcast colour specification box	'bcol' (0x62636f6c)	Required	This box specifies the broadcast colour specification
Mastering display metadata box	'dmon' (0x646d6f6e)	Required	This box describes the display characteristics of the mastering display

4) Clause M.4

Replace clause M.4 with the following text:

M.4 Elementary stream marker box (superbox)

This superbox specifies all parameters required to define an elementary JPEG 2000 access unit. If this superbox exists, it shall contain one frame rate coding box, one maximum bit rate box, one time code box and one broadcast colour specification box.

This superbox may contain other optional boxes. One or two contiguous codestreams must immediately follow the elsm superbox as defined by the coding boxes contained in the elsm superbox.

The type of an elementary stream marker box shall be 'elsm' (0x656c 736d). The contents of the elementary stream marker box are as in Figure M.1.

frat: Frame rate coding box. This box specifies the frame rate in frames per second. The format of this box is specified in M.4.1.

brat: Maximum bit rate box. This box specifies the maximum bit rate of the elementary stream in bits per second. The format of this box is specified in M.4.2.

fiel: Field coding box. This box specifies the field order if the access unit contains two fields. The format of this box is specified in M.4.3. This box is optional.

tcod: Time code box. This box specifies the time code of the access unit in the elementary stream marker superbox. The format of this box is specified in M.4.4.

bccl: Broadcast colour specification box. This box specifies the colour space of the access unit. The format of this box is specified in M.4.5.

dmon: Mastering display metadata description box. This box specifies the characteristics of the content mastering display. The format of this box is specified in M.4.6.

5) Table M.2

Replace Table M.2 with the following table.

Table M.2 – Code for identifying colour specification

Code	Colour specification
0x00	Unspecified
0x01	IEC 61966-2-1:1999
0x02	Rec. ITU-R BT.601-6
0x03	Rec. ITU-R BT.709-5
0x04	See Tables M.3, M.4 and M.5
0x05	ISO 26428-1 (X'Y'Z')
0x06	Rec. ITU-R BT.2020
0x07	SMPTE ST 2084
0x08-0xFF	Reserved

6) Clause M.4.6

Add clause M.4.6 after Table M.5.

M.4.6 Mastering display metadata box (required)

This box specifies the characteristics of the mastering display metadata. The type of the mastering display metadata box shall be 'dmon' (0x646d6f6e) and contents of the box shall have the format as in Figure M.7:

X _{c0}	Y _{c0}	X _{c1}	Y _{c1}	X _{c2}	Y _{c2}	X _{wp}	Y _{wp}	L _{min}	L _{max}
-----------------	-----------------	-----------------	-----------------	-----------------	-----------------	-----------------	-----------------	------------------	------------------

Figure M.7 – Mastering display metadata

X_c and **Y_c** are 2-byte unsigned integers that specify the normalized x and y chromaticity coordinates, respectively, of the colour primary component c of the mastering display in increments of 0.00002, according to the CIE 1931 definition of x and y as specified in ISO 11664-1 (see also ISO 11664-3 and CIE 15). For describing mastering displays that use red, green, and blue colour primaries, it is suggested that index value c equal to 0 should correspond to the green primary, c equal to 1 should correspond to the blue primary, and c equal to 2 should correspond to the red colour primary. The values of X_c and Y_c shall be in the range of 0 to 50 000, inclusive.

X_{wp} and **Y_{wp}** are 2-byte unsigned integers that specify the normalized x and y chromaticity coordinates, respectively, of the white point of the mastering display in normalized increments of 0.00002, according to the CIE 1931 definition of x and y as specified in ISO 11664-1 (see also ISO 11664-3 and CIE 15). The values of X_{wp} and Y_{wp} shall be in the range of 0 to 50 000.

L_{min} and **L_{max}** are 4-byte unsigned integers that specify the nominal maximum and minimum display luminance, respectively, of the mastering display in units of 0.0001 candelas per square metre. L_{min} shall be less than L_{max}.

At minimum luminance, the mastering display is considered to have the same nominal chromaticity as the white point.